# ACCUD

## ACCURATE MEASUREMENT




See full product range at: accud.com.au

# Digital Force Gauge

Series DF




## Features

For pull and push measurement
Adjusting the display direction automatically
With overload protection
Peak and real-time working mode
Unit: mN, N, gf, kgf, ozf, lbf
Memory: 1000
Power off automatically
Low and high limits setting with judgement
With software, can show the force graph

## Specifications

| Part No | Specification |
|---|---|
| AC-DF10K | Range: 10000N<br>Resolution: 1N<br>Accuracy: ±0.2% x FS (full scale)<br>Power: rechargeable battery<br>Dimension: 153x73x34mm<br>Weight: 700g<br><br>Included accessories<br>Main unit: 1pc<br>Sensor: 1pc<br>Charger: 1pc<br>Software: 1pc<br><br>Optional accessories<br>M12 Flat clamp(for DF2K, DF5K and DF10K): DF2K-FC<br>M12 Extension (for DF2K, DF5K and DF10K): DF2K-ER<br>M12 Pull clamp (for DF2K, DF5K and DF10K): DF2K-PC<br>M18 Flat clamp (for DF20K): DF20K-FC<br>M18 Extension (for DF20K): DF20K-ER<br>M18 Pull clamp (for DF20K): DF20K-PC<br>Wireless printer: PR100 |

© 2026 M Gamer Pty Ltd

| Part No | Specification |
| --- | --- |
| AC-DF20K | Range: 20000N<br>Resolution: 1N<br>Accuracy: ±0.2% x FS (full scale)<br>Power: rechargeable battery<br>Dimension: 153x73x34mm<br>Weight: 700g<br><br>Included accessories<br>Main unit: 1pc<br>Sensor: 1pc<br>Charger: 1pc<br>Software: 1pc<br><br>Optional accessories<br>M12 Flat clamp(for DF2K, DF5K and DF10K): DF2K-FC<br>M12 Extension (for DF2K, DF5K and DF10K): DF2K-ER<br>M12 Pull clamp (for DF2K, DF5K and DF10K): DF2K-PC<br>M18 Flat clamp (for DF20K): DF20K-FC<br>M18 Extension (for DF20K): DF20K-ER<br>M18 Pull clamp (for DF20K): DF20K-PC<br>Wireless printer: PR100 |
| AC-DF2K | Range: 200N<br>Resolution: 0.5N<br>Accuracy: ±0.2% x FS (full scale)<br>Power: rechargeable battery<br>Dimension: 153x73x34mm<br>Weight: 700g<br><br>Included accessories<br>Main unit: 1pc<br>Sensor: 1pc<br>Charger: 1pc<br>Software: 1pc<br><br>Optional accessories<br>M12 Flat clamp(for DF2K, DF5K and DF10K): DF2K-FC<br>M12 Extension (for DF2K, DF5K and DF10K): DF2K-ER<br>M12 Pull clamp (for DF2K, DF5K and DF10K): DF2K-PC<br>M18 Flat clamp (for DF20K): DF20K-FC<br>M18 Extension (for DF20K): DF20K-ER<br>M18 Pull clamp (for DF20K): DF20K-PC<br>Wireless printer: PR100 |
| AC-DF5K | Range: 500N<br>Resolution: 1N<br>Accuracy: ±0.2% x FS (full scale)<br>Power: rechargeable battery<br>Dimension: 153x73x34mm<br>Weight: 700g<br><br>Included accessories<br>Main unit: 1pc<br>Sensor: 1pc<br>Charger: 1pc<br>Software: 1pc<br><br>Optional accessories<br>M12 Flat clamp(for DF2K, DF5K and DF10K): DF2K-FC<br>M12 Extension (for DF2K, DF5K and DF10K): DF2K-ER<br>M12 Pull clamp (for DF2K, DF5K and DF10K): DF2K-PC<br>M18 Flat clamp (for DF20K): DF20K-FC<br>M18 Extension (for DF20K): DF20K-ER<br>M18 Pull clamp (for DF20K): DF20K-PC<br>Wireless printer: PR100 |

© 2026 M Gamer Pty Ltd